

EZFlow EPS Aggregate System Design Table

<i>EZFlow Configuration</i>	<i>Bundle Diameter (in)</i>	<i>Number of Bundles</i>	<i>Number of 4" Diameter Pipes</i>	<i>Trench Width (in)</i>	<i>Allowable Effective Absorption Area (Divisor) (sf/lf)</i>
1204V	12	4	1	12	11
1203V	12	3	1	12	8.6
1202V	12	2	1	12	5.7
1803V	18	3	1	18	11
1802V	18	2	1	18	9.3
1801V	18	1	1	18	5
1208V	12	8	1	24	11
1207T	12	7	1	24	11
1206V	12	6	1	24	10
1205T	12	5	1	24	9.5
1209V	12	9	1	36	11
1802H	18	2	1	36	7.1
1805T	18	5	1	36	11
1804V	18	4	1	36	11
1803T	18	3	1	36	11